

SYSTEMS SPECIFICATIONS

STRUCTURED CABLING
Horizontal Cabling
Requirements
Copper cable shall be Category 6 plenum rated cable (blue in Color) for all work station drops.
Copper cable shall be Category 6 plenum rated cable (White in Color) for all Security camera drops.
Copper cable shall be Category 6 plenum rated cable (Yellow in Color) for all Wifi drops.
Approved Category 6 cables are as follows.
Superior Essex Cat6 Plenum Part #s
Mohawk Cat6 Plenum Part #s
Berk-Tech Cat6 Plenum Part #s
General Cat6 Plenum Part #s

- Connector shall be Leviton part # 61110-ROG eXTreme 6 connector for all workstation drops.
Connector shall be Leviton part # 61110-RW6 eXTreme 6 connector for all Security camera drops.
Connector shall be Leviton part # 61110-RY6 eXTreme 6 connector for all Wifi drops.
Contractor shall provide Moore Public Schools, Technology Department, one 5' category 6 patch cord, (blue in color) for each category 6 work station cable installed.
Contractor shall provide Moore Public Schools, Technology Department, one 10' category 6 patch cord, (blue in color) for each category 6 work station cable installed.
Contractor shall provide Moore Public Schools, Technology Department, one 5' category 6 patch cord, (White in color) for each category 6 Security Camera cable installed.
Contractor shall provide Moore Public Schools, Technology Department, one 10' category 6 patch cord, (White in color) for each category 6 Security Camera cable installed.
Contractor shall provide Moore Public Schools, Technology Department, one 5' category 6 patch cord, (Yellow in color) for each category 6 Wifi cable installed.
Contractor shall provide Moore Public Schools, Technology Department, one 10' category 6 patch cord, (Yellow in color) for each category 6 Wifi cable installed.
Each cable shall be terminated on the patch panel in data closets.
All Category 6 connectors shall be placed into QuickPort faceplates at the workstation end.
Faceplate shall be Leviton part # 41080-6wp
No substitutions.

Communications Backbone Cabling
Requirements - Optical fiber
1 Optical fiber cable shall be run from the MDF to each IDF.
Fiber shall be terminated with LC connectors.
Optical fiber cable shall be plenum rated Laser Optimized 50 micron Multi Mode distribution fiber.
Optical fiber cable shall be an OM3 rated cable guaranteed to support 10 Gigabit Ethernet for 300 meters using 850 nm wavelength.
Optical fiber cable shall have 24 strands using industry standard color coding.
Optical fiber cable shall have a flame retardant and low smoke FEP jacket.
Optical fiber cable shall support 10GBase-SX applications for the life of the system.
Optical fiber cable shall be armor jacketed or protected inside plenum rated plastic inner duct orange or aqua in color.
MIC Tight-buffered 024T88-33180-A3
No substitutions.

Requirements - Copper backbone
6 Cat 6 cables shall be run from the MDF to each IDF.
3 Cat 6 cables shall be run from the phone Dmark to the MDF.
Copper cable shall be Category 6 cable. Green in color
Connector shall be Leviton part # 61110-RV6 eXTreme 6 connector.
Each cable shall be terminated on the patch panel in data closets.
Each cable end shall be terminated using the T568B pin/pair assignment.
No substitutions.

Cable Installation
Properly support horizontal cables in ceiling every 4'-5' using J-Hooks or cable tray only.
Place horizontal cables in pathways and spaces dedicated for communications cables.
Provide 30' of slack at station end in ceiling and not inside wall.
Slack shall be rolled neatly in a 2' loop and hanging from a j-hook in ceiling above drop location.
Cat 6 data cables are to be terminated using the T568B standard.
Leviton face plates that support 6 snap in jacks will be used with Leviton snap in blanks in unused slots.
Ensure terminations are at 180 degrees to the jack with no more than 1/2" un-twisting and no more than 1/2" un-jacking and are in accordance with manufacturer's recommendations.
Ensure terminations have no un-twisting and that tower separators are utilized to separate pairs.

- Ensure pulling tensions of cables are not exceeded.
Maintain proper cable bend radius of 4 times the cable's outer diameter during placement.
No splices are permitted.
No link shall exceed 90 meters. Contractor is responsible for verifying proper footages.
Pull one additional "Mule Tape" or 1/2" Nylon rope when pulling cables through any conduit utilizing existing pull string.
Mule Tape or Nylon rope is to be pulled into conduit separately and after all other cables have been installed.
Install sleeves when puncturing walls.
Cable shall not be installed between cinder block walls and roof decking.
Cable shall not be installed between red iron and roof decking.
Firestop all sleeves and conduit openings after cable installation.
Terminate all pairs and conductors at all ends according to manufacturer's instructions following color code sequence.
No splices are permitted in any fiber optic cable except when terminating connectors.
Terminate all Fiber pairs.

- Optical fiber cable shall be installed in the fiber panels in accordance with the manufacturer's instructions.
Optical fiber Back bone cable length shall not exceed 300 meters.
Copper backbone cable length shall not exceed 90 meters.
All back bone cables (Fiber and Copper) shall have 20' of slack at both ends.
Coming rack mount fiber patch panels are to be used where applicable.
Outdoor rated fiber will be used for all outdoor fiber runs.
Stress relief cable and the appropriate building fastener will be used on all aerial runs.
All aerial cables will be fastened to the stress relief cables.
3' conduit is to be used for all buried runs, accessible at each end, with a pull string inside.
A trace wire and warning tape will be buried with all buried runs.
All bends in conduit will be made with sweeps.
Back bone cabling shall utilize a star topology with no more than 2 levels of backbone.
Utilize VELCO ONLY in all closets.
Install all components in a neat and workmanlike manner.
Install all horizontal cables and termination frames in accordance with manufacturer's recommendations.

- Labeling
Label shall be a rap type with number printed multiple times enabling print to be legible from any angle.
Machine label all termination panels and face plates with cabinet and cable number.
Termination panels shall be labeled in numerical order.
A single drop will be labeled a total of four times. The labels will be located on the patch panel in the rack, on both ends of the cable, and on the face plate at the work station end.
All 5' patch cables will be labeled at both ends. 5' cables will be installed at the cabinet.
Numbering scheme will be 00-000 where the first two digits are the cabinet number and the last three are the drop number.
Camera drop labels numerically start at 500 in each cabinet.
Wifi drop labels numerically start at 800 in each cabinet.

Test
Test results for all Category 6 copper and fiber optic cables shall be provided to Moore Public Schools, Technology department.
End of Section

Communications Equipment Room Fittings
Equipment rack
Free standing equipment rack shall be Chatsworth #55053-703.
Free standing racks shall be sized to accept 19" spaced equipment and handle a total weight load of 1, 000 pounds.
Free standing racks shall have 3" side rails tapped on both sides with universal hole patterns for threaded 12-24 screws.
No substitutions.
Copper Patch panels
Patch panel shall be a Leviton #49255-H24 Quick Port 110 panel with cable management bar.
Patch panel shall have 24 ports taking up 1 rack mount unit.
No substitutions.

Horizontal cable management
Horizontal cable manager shall be a 2 RU Chatsworth part #30130-719.
No substitutions.
Vertical cable management
Vertical cable manager shall be Chatsworth part #30095-703.
No substitutions.
Optical fiber patch panel / enclosure
Optical fiber enclosure shall be Corning LC loaded rack mount panel.
CCH-04U
CCH-01U
CCH-CP24-E4
SOC-LC-900-OM4

- No substitutions.
Ladder racking
Ladder racking shall be Chatsworth #10250-718.
The appropriate Chatsworth mounting hardware shall be used.
No substitutions.
Power protection power strips
PDU's are to be placed in all data racks.
PDU shall have overload protection and easy to reset circuit breaker.
PDU shall be rack mountable.
PDU shall be constructed from 18 AWG steel.
PDU shall have light emitting diodes to indicate "Power On" and "Ground/Polarity OK" feature.
PDU shall be rated for 20 Amps and have a 12' L5-20P plug and ten 5-20R receptacles.
No substitutions.

- Free standing racks
Assemble free standing racks according to manufacturer's instructions.
All racks must be attached to the floor in four places using appropriate floor mounting anchors.
All rack must be secured to the adjacent wall using ladder rack to stabilize the top of the rack.
Racks shall be grounded to the telecommunications bus bar using #6 AWG green insulated solid copper wire.
Ladder rack
Ladder rack shall be attached to the top of the rack to deliver cables to the rack.
Ladder racking shall be supported every 5' with 3/8" threaded rod anchored and secured to permanent ceiling structure.
Loading of cable rack shall not exceed 6" depth and should have retainers every 12" to prevent cables from spilling over the sides.
Where ladder racking butts up against wall the appropriately sized wall mount bracket shall be utilized.
Ladder rack shall extend vertically up wall and through drop ceiling to gain access to cavity above drop ceiling.
Ladder racking shall utilize all appropriate radius drop stringers, corner bends and other devices to maintain cable bend radius when entering and exiting racks, cabinets and drop ceilings.
Mating pieces of ladder racking together shall utilize appropriate butt splice and junction splice kits.
All cut and exposed sharp ends shall utilize a plastic end cap to prevent injury.

- Cable management
Vertical cable manager shall be installed on every rack vertical rail.
Horizontal wire managers shall be utilized above and below every copper and fiber patch panel.
All cables shall sweep in and out of any cable management product without a deformation of cable jacket.
Ensure cables are properly supported when using cable management to ensure cables do not sag.
Utilize Velcro ONLY for securing of cables on cable management.
Copper and Fiber patching panels
Route all cables to backside of termination panels in an asymmetrical orientation to ensure cable bundles are split evenly.
Utilize rear wire management bars for supporting cables into point of termination.
Secure all cables on all panels using Velcro ONLY to prevent cables from pulling away.

- Quality Assurance
Install all components as directed by Manufacturer's installation guidelines.
All products shall bear the mark of UL or ETL for performance level.
System installation shall meet all applicable Local/State codes and safety requirements where project is located.
All products shall be new and un-used in original packaging.
Follow and adhere to installation practices specified by the applicable Telecommunications Industry Association standards.
Follow and adhere to installation practices specified by BICSI Information Transport System Installation.
Follow and adhere to installation practices specified by BICSI Telecommunications Distribution Methods.
Follow and adhere to installation practices specified by NFPA-70 National Electric Code.
Follow and adhere to installation practices specified by the Manufacturers.
Contractor shall make available all ceiling and termination work for inspection by Manufacturer's representative or owner's representative.
Contractor shall replace all defective components.

- Bidder/Installer Qualifications
Bidding Contractor shall be a licensed to install telecommunications systems in the state where work will be performed.
Bidding Contractor shall be Leviton certified for at least one year.
Bidding Contractor shall have a minimum of 5 years experience installing structured cabling for telecommunications.
Bidding Contractor shall have the capability to bond project in its entirety.
Bidding Contractor shall be able to provide insurance at the request of the owner.
Installer shall have an onsite supervisor and one technician who are certified by the Manufacturer to install the Manufacturer's telecommunications products.
Communications Contractor shall have an RCDD on staff for at least one year, to certify that the Communications System can support the required applications on the various cabling media.

- Installer shall have obtained Leviton certification from the Manufacturer within 1 year prior to performing the Work.
Delivery, Storage, and Protection
Communications Contractor shall ensure that materials delivery to work area shall be coordinated with construction site manager responsible for materials distribution to all trades.
Communications Contractor is responsible for all materials, tools and vehicles left on the job site.
Communications Contractor shall coordinate a disposal bin for the removal of all trash produced by the Communications Contractor personnel during the project.
Communications Contractor shall ensure materials are stored in an environmental area where:
Temperature does not exceed 120 degrees Fahrenheit nor below 32 degrees Fahrenheit.
Humidity does not exceed 80 %.
No direct exposure to sunlight.
Follow Manufacturer's recommendations for handling of materials.
Warranty
Communications Contractor shall provide a 1 year parts and labor warranty against defective workmanship and/or system component failure.
Communications Contractor shall execute a Lifetime Applications Assurance Warranty for parts and labor to support stated applications from the connectivity Manufacturer.

Intercom System Specifications
Part 1 - General
1.01 System Manufacture
Intercom System Manufacturer shall be Telecor or Rauland Telecenter U IP (Match existing system.)
Cable Manufacturer shall be Belden or Equivalent.
Locations where Telecor equipment is required.
Locations where TelecenterU Equipment is required.
1.02a Intercom Systems Equipment Description
Intercom call in button shall be momentary close and compatible with existing intercom system.
Intercom ceiling speakers shall be Manufacture Clarity Model # S-522.
Intercom outside paging horn shall be Manufacture Rauland Borg 3601.
Locations where Telecor equipment is required.
Locations where TelecenterU equipment is required.
1.02b Intercom Systems Equipment Description
Classroom Intercom Equipment
Call button shall be Part # 603302 Dual Level call switch.
Ceiling speakers shall be Part # BAFKIT2XL6RJ - 8 Ohm ceiling tile replacement speaker with RJ45 connector.
IP Classroom Module shall be TCC2011 IP Module.
Hallway/Commons/Outside Intercom Equipment
TCC2022-IP Zone page module.
BAFKIT2XZL- 25 volt ceiling the replacement paging speaker.
Rauland Borg 3601 - Loud paging horn.

- Systems Installation
All non-IP cabling shall be shielded and have a minimum of 5 conductors.
All network IP cabling shall be Cat6.
All wire shall be shielded and have a minimum of 5 conductors.
All circuits and wiring shall be labeled at all terminating ends.
All devices shall be mounted according to the manufactures specifications.
All devices shall be properly adjusted and tested prior to job completion.
All room circuits shall run from the intercom system to the call button then to the room speaker.
All extra speaker wire taps shall be insulated.
All rooms shall be individually wired and terminated at the intercom system on individual points.
All rooms shall be tested to verify proper room number programming and operation.
All call buttons shall be labeled with their corresponding system point number.
Protective grommets shall be installed on all conduits to protect wire.
All wire shall be run in J hooks above ceiling with a minimum space of 4" from ceiling deck.
All wire ran between building shall be in conduit and shall be direct burial cable.
Installer shall supply the electrical and or masonry contractors with specialty back boxes and coordinate with them to ensure that all necessary conduits, back boxes, etc. are installed in the proper locations.
Follow and adhere to installation practices specified by NFPA-70 National Electric Code, Edition 2008.

- Quality Assurance
Follow and adhere to installation practices specified by the Manufacturers.
1.04 Quality Assurance
1.03.01 Qualifications
Install all components as directed by Manufacturer's installation guidelines.
All products shall bear the mark of UL or ETL for performance level.
System installation shall meet all applicable Local/State codes and safety requirements where project is located.
All products shall be new and un-used in original packaging.
1.03.02 Bidder/Installer Qualifications
Bidding Contractor shall have a minimum of 5 years experience installing school intercom systems.
Bidding contractor shall be able to provide insurance at the request of the owner.
1.05 Delivery, Storage, and Protection
Contractor shall ensure that materials delivery to work area shall be coordinated with construction site manager responsible for materials distribution to all trades.
Contractor is responsible for all materials, tools and vehicles left on the job site.
Follow Manufacturer's recommendations for handling of materials.

- 1.06 Scheduling
Contractor shall provide a detailed construction schedule with hard dates for completion of roughing in cables, terminations and testing once scheduling sequence has been determined to the Owner's Project Manager.
1.07 Warranty
Contractor shall provide a 1 year parts and labor warranty against defective workmanship and/or system component failure.
Part 3 - Execution
3.01 Field Quality Control
Contractor shall make available all ceiling and termination work for inspection by Manufacturer's representative or owner's representative.
Contractor shall replace all defective components.
3.02 Adjusting
No additional work outside of the contract scope of work shall be completed without the approval of the Owner or Owner's representative.
3.03 Protection
It is the responsibility of the Contractor to ensure equipment is protected from dust and water during the project with appropriate materials.
Remove all protective covers and protective materials from equipment prior to turnover to Owner.
3.04 Schedules
Coordinate work with Owner's project manager and follow scheduling sequence as established by Owner's project manager.
It is recommended that the Contractor schedule closely with any other systems contractor to ensure turnover date is met.
Contractor bidding will supply the electrical and or masonry contractors with any specialty back boxes such as clock recessed back boxes etc. and coordinate with them to ensure that all necessary conduits, back boxes, etc. are installed in the proper locations.

1.04 Submittals
1.04.01 Prior to installation
Show complete map of system design for approval by Owner.
3.02 System Requirements
Intercom system shall be capable of communicating to all rooms and shall have adequate number of room points as to not double up on any given point.
End of Section

Intercom System Installation Completion Check List
Part 1 - General
1.01 Section Includes
Intercom System Completion Check List
1.02 Completion Check List
Main control panel has a map of the entire system inside and a copy has been given to Jack Phillips with MPS.
All intercom programming such as bell times, tornado drill alert, etc has been checked and is correct.
Intercom has been tested for proper operation.
All rooms have been tested to verify proper description at console.
All speakers have been tested to verify proper operation and volume.
All extra speaker wires have been tapped or insulated.
All call buttons are labeled and have been tested for proper operation.
End of Section

Clock System Specifications
Part 1 - General
1.01 System Manufacture
Clock Equipment shall match existing system.
Locations where Telecor equipment is required.
Advanced Cabling, Inc - 405-418-4322
High-Tech Tronics, Inc - 405-495-0215
1.02 Intercom Clock Systems Equipment Description
Intercom Digital Clocks shall be hard wired and may not use battery power for its primary power source.
Clocks shall be 4 inch and be compatible with existing system.
Clocks must be compatible with existing clock system.

AGP the Abila Griffin Partnership L.L.C.

201 N. BROADWAY SUITE 210 MOORE, OK. 73160 405.735.3477 AGP@theAGP.net www.theAGP.net

KFC ENGINEERING STRUCTURAL

SALAS O'BRIEN MECHANICAL / ELECTRICAL

MOORE PUBLIC SCHOOLS BOARD OF EDUCATION MOORE, OKLAHOMA



OFFICE ADDITION - NORTHMOOR ELEMENTARY SCHOOL

sheet no:

T501

OWNERSHIP USE OF DOCUMENTS: AGP EXPRESSLY RESERVES ITS COPYRIGHT AND OTHER PROPERTY RIGHTS OF ALL PLANS AND DRAWINGS DESIGNED AND/OR PRODUCED. PLANS AND DRAWINGS ARE NOT TO BE REPRODUCED IN ANY FORM OR MANNER WITHOUT THE EXPRESSED WRITTEN CONSENT OF AGP.

Salas O'Brien logo and contact information: 2800 Van Buren St., Suite 2635 Norman, OK 73072 Salas O'Brien Registration: CA# 7058 Expiration Date : 6/30/2023 Salas O'Brien Project Number: 2023-01177-00